

B3 Portable Radio

The Restaurant business is fast paced, and quality communications is key to quality service. The B3 Two Way Radio from BTG enhances efficiency by allowing hosts, managers, kitchen and wait staff to instantly communicate with a small and Rugged but still lightweight device. The B3's unique impact resistant design stands out among its competitors as a clear choice for most demanding users. A long Life battery and 4 Watts of power, ensure that the radio not only survives the entire day, but also has the coverage of your entire site.

Features

- High Quality Audio
- 4 Watts of UHF Power
- Channel Annunciation
- VOX
- Battery Power Indicator
- Scrambler
- Whisper Mode
- Auto High/Low Power
- BCL
- TOT
- CTCSS/CDCSS
- Narrow Band
- Scan
- Squelch
- Wired Clone
- Two Programmable Keys
- Double Slot Fast Charge
- Rugged Design



3
B

G
T
B



General	
Frequency range	VHF: 136-174MHz UHF: 400-470MHz; 450-520MHz
Channel Spacing	12.5kHz / 25kHz
Power supply	7.5V
Operating temperature	-25~55
Number of Channels	16 (15+S)
Battery (Standard)	1800mAh (Li-ion Battery)
Dimensions (W X H X D)	105x62x35mm
Weight	233g
Receiver	
Sensitivity (12 dB SINAD)EIA	0.15uV / 0.18uV
Intermodulation EIA	65dB
Adjacent channel selectivity	70dB / 60dB
Spurious rejection	≥70dB
Rated Audio	1W
Audio distortion @ rated audio	≤5%
Audio response (300-3000Hz)	≥70dB
Transmitter	
Power output	UHF : 4W/1W; VHF : 5W/1W
Modulation Type	16kΦF3E / 8kΦF3E
Modulation limiting	≤5KHz / ±2.5KHz
FM Hum and noise	-45dB / -40dB
Conducted/Radiated emission	-36dBm
Adjacent channel power	-70dB / -60dB
Audio distortion	≤5%

NOTE: The specifications may be subject to change without notice due to advancement in technology, for more detailed information, please contact BluFi Wireless USA.

Compatible Accessories



Charger Adapter



Desktop Charger



Ear-piece Mic



Antenna(UHF)



Li Battery



Belt Clip



41 Odell Schoo Road, Suite I,
Concord, NC 28027
(704) 412-7555
www.techsources.us
sales@techsources.us